

WIRTANEN ELECTRIC LTD.

5635 Gateway Blvd.
Edmonton, Alberta T6H 2H3 Canada
Phone: (780) 434-8421 Fax: (780) 437-2658
Canada-U.S. Toll Free 1-800-661-9462
Website: www.wirtanen.com



FLUKE 99B DUAL CHANNEL - 100 MHZ SCOPEMETER

SPECIFICATIONS

- Bandwidth: 100 MHz Dual Channel
- Sample Rate: 25 Megasamples/second
- Autoset: Automatically sets Voltage, Time & Trigger
- Multimeter Display: 3 2/3 Digits (> 3000 Counts)
- True RMS Volts: AC or AC+DC up to 600V (1700V Pk-Pk)
- Resistance: 30 ohm to 30 Mohm
- Diode Test: up to 2.8V
- Continuity Beeper
- Time/Division: 10 ns/div to 60 sec/div
- Volts/Division: 1 mV/div to 100 V/div
- Current Probe Scaling
- Digital Delay or Pre-Trigger: By Number of Cycles, Events, Time or Zoom Mode
- Special Multimeter Modes: Min Max Average Record with Time Stamp, Relative (zero), dBm, dBV, dBW, Audio Watts, %Scale, Frequency, %Duty Cycle, Smoothing™, Change Alert™
- Oscilloscope Cursors: Display 5 Simultaneously
- Glitch Capture: ≥ 40 ns
- Waveform Processing: Average, Min Max, Record, Variable Persistence
- Waveform Memory: Store & Recall 20 Waveforms
- Set-up Memory: Store & Recall 40 Front Panel Set-Ups
- Waveform Mathematics: Add, Subtract, Multiply, Invert, Filter or Integrate Waveforms
- Signal Generator Output: Sine wave or Square wave
- Component Tester Output: voltage or current ramp



Power Supply

- Internal Battery Pack: NiCad, 4.8V
- Operating Time: 4 hours/typical
- Line Voltage Adapter/Battery Charger: standard

Mechanical Data

- Size: 2.4" H x 5.1" W x 10.2" L
- Weight: 3.3 lbs

RENTING

The Smart Way
To Get Things Done.

Wirtanen Electric Ltd. * To Order Call (780) 434-8421 or 800-661-9462